

Raw OLAP data formats

OLAP produces several data formats, which are intended to be replaced by their final format, such as HDF5. The formats below are not officially supported and subject to change without notice.

Beamformed Data

Beamformed data can be recorded as either complex voltages (yielding X and Y polarisations) or one or more stokes. In either case, a sequence of blocks will be stored, each of which consists of a header and data. The header is defined as:

```
struct header {
    uint32_t sequence_number; /* big endian */
    char padding[508];
};
```

in which sequence_number starts at 0, and is increased by 1 for every block. Missing sequence numbers implies missing data. The padding can have any value and is to be ignored.

Complex Voltages

As of 2010-09-20, the following block format is used:

```
struct block {
    struct header header;

    /* big endian */
    fcomplex voltages[SAMPLES][2][SUBBANDS][CHANNELS];
};
```

Below is a list of the constants used, and which key they represent in the parset file as produced by OLAP:

SAMPLES	The number of time samples in a block	OLAP.CNProc.integrationSteps
SUBBANDS	The number of subbands (beamlets) specified	len(Observation.subbandList)
CHANNELS	The number of channels per subband	Observation.channelsPerSubband

Types

A 'float' is a 32-bit IEEE floating point number. An 'fcomplex' is a complex number defined as

```
struct fcomplex {
    float real;
    float imag;
};
```

Last
update:
2010-10-21 13:10 public:documents:raw_olap_data_formats https://www.astron.nl/lofarwiki/doku.php?id=public:documents:raw_olap_data_formats&rev=1287666610

From:
<https://www.astron.nl/lofarwiki/> - **LOFAR Wiki**

Permanent link:
https://www.astron.nl/lofarwiki/doku.php?id=public:documents:raw_olap_data_formats&rev=1287666610

Last update: **2010-10-21 13:10**

