

# Starting Out With AIPS Tutorial

James M Anderson

This tutorial session is intended to get people familiar with the basic concepts of radio interferometry. The student will be introduced to interferometry data, visibilities, the  $(u,v)$  plane, calibration, and imaging.

## Step 1 --- Figure Out What to Observe (Reduce)

I decided to try to make an image of the Sun, as the Solar KSP is a significant part of GLOW. The NRAO image archive has a nice image of the Sun at 1400 MHz located at <http://images.nrao.edu/8>



Image courtesy of NRAO/AUI

Let's try to reduce the data ourselves.

## Step 2 --- Download the Data From the Archive

Conveniently, the NRAO image archive gives details about the observations used to make the image, so I downloaded the data from the NRAO data archive, making sure to select the "AIPS friendly" filename option.

This has resulted in two files on my hard drive in my current directory:

```
ls -l
total 54164
-rw-r-- 1 anderson zeall 21002240 2008-11-11 14:40 GD_1
-rw-r-- 1 anderson zeall 34392064 2008-11-11 14:41 GD_2
```

## Step 3 --- Start up AIPS

```
aips
```

I have chosen to use user ID 100, at semi-random selection.

At first, most of the arcane syntax used to enter commands to AIPS will be difficult. As this is a tutorial session which intends to teach you about radio interferometry, and not how to use AIPS, we will gloss over the technical challenges of interacting with AIPS.

In AIPS you the user interact with something called POPS. You give POPS information by setting variables called ADVERBS to specific values. You can tell POPS which TASK you plan to run by setting a TASK ADVERB. If you want to check the values of ADVERBs for the current TASK, you ask for INPUTS. Because POPS will try to figure out what you mean if you only input the first few letters of an ADVERB or VERB, you can often abbreviate this to just INP. Also note that since AIPS is case-insensitive by default, you could also just type inp. If you want help on a specific topic, ask for HELP. If you want even more explanation for something, say EXPLAIN. If you don't know what it is you are trying to do, but you have some vague notion, say APROPOS SOMETHING. Note that apostrophes, and in certain locations, the lack of an apostrophe are significant.

## Step 4 --- Initial look at data

### FILLM

The AIPS task to read raw VLA data into AIPS is called FILLM.

```
dowait=true
dohist=1
docrt=132
dotv=1
task 'fillm'
default
datain = 'PWD:GD_
nfiles=0
ncount=2
vlamode='S '
doweight=10
doconcat=true
douvcomp=0
cparm(2)=16
cparm(4)=28
cparm(8)=10./60
go
```

This sets us up to read the data, sets the VLA mode to Solar, tells AIPS not to change the source if the position appears to be moving (which the Sun does), sets the shadowing limit to 28 meters, and sets the CL table interval to 10 seconds.

### Header information

pcat

```

AIPS 1: Catalog on disk 1
AIPS 1:  Cat Usid Mapname      Class  Seq Pt      Last access      Stat
AIPS 1:   1  100 19810926      .L BAND.      1 UV 14-NOV-2008 21:35:31

```

getn 2  
imhe

```

AIPS 1: Image=MULTI      (UV)      Filename=19810926      .L BAND.      1
AIPS 1: Telescope=VLA      Receiver=VLA
AIPS 1: Observer=GD      User #= 100
AIPS 1: Observ. date=26-SEP-1981      Map date=14-NOV-2008
AIPS 1: # visibilities      556884      Sort order TB
AIPS 1: Rand axes: UU-L-SIN  VV-L-SIN  WW-L-SIN  BASELINE  TIME1
AIPS 1:      SOURCE  FREQSEL
AIPS 1: -----
AIPS 1: Type      Pixels  Coord value      at Pixel      Coord incr      Rotat
AIPS 1: COMPLEX      3      1.0000000E+00      1.00      1.0000000E+00      0.00
AIPS 1: STOKES      4      -1.0000000E+00      1.00      -1.0000000E+00      0.00
AIPS 1: FREQ      1      1.4461500E+09      1.00      1.2500000E+07      0.00
AIPS 1: IF      1      1.0000000E+00      1.00      1.0000000E+00      0.00
AIPS 1: RA      1      00 00 00.000      1.00      3600.000      0.00
AIPS 1: DEC      1      00 00 00.000      1.00      3600.000      0.00
AIPS 1: -----
AIPS 1: Coordinate equinox      0.00
AIPS 1: Maximum version number of extension files of type HI is      1
AIPS 1: Maximum version number of extension files of type AN is      1
AIPS 1: Maximum version number of extension files of type NX is      1
AIPS 1: Maximum version number of extension files of type SU is      1
AIPS 1: Maximum version number of extension files of type FQ is      1
AIPS 1: Maximum version number of extension files of type CL is      1
AIPS 1: Maximum version number of extension files of type TY is      1
AIPS 1: Maximum version number of extension files of type WX is      1
AIPS 1: Maximum version number of extension files of type OF is      1
AIPS 1: Keyword = 'CORRMODE' value = '      '
AIPS 1: Keyword = 'VLAIIFS ' value = 'AC      '
AIPS 1: Keyword = 'CORRCOEF' value =      -1

```

## LISTR --- scan listing

```

default listr
task 'listr'
indi 1
getn 2
optype 'scan'
docrt=132
go

```

v1b054 LISTR(31DEC08) 100 14-NOV-2008 21:42:46 Page 1  
 File = 19810926 .L BAND. 1 Vol = 1 Userid = 100  
 Freq = 1.446150006 GHz Ncor = 4 No. vis = 556884  
 Scan summary listing

Scan	Source	Qual	Calcode	Sub	Timerange	FrqID
START VIS	END VIS					
1	1148-001	: 0000	C	1	0/13:53:25 - 0/13:53:25	1
1	351					
2	1148-001	: 0000	C	1	0/13:53:35 - 0/13:54:35	1
352	2808					
3	SUN	: 0000		1	0/13:59:05 - 0/13:59:35	1
2809	4212					
4	SUN	: 0000		1	0/14:05:15 - 0/14:09:35	1
4213	13689					
5	1148-001	: 0000	C	1	0/14:18:05 - 0/14:19:35	1
13690	17199					
6	SUN	: 0000		1	0/14:20:15 - 0/14:24:35	1
17200	26676					
7	SUN	: 0000		1	0/14:30:05 - 0/14:34:35	1
26677	36504					
8	1148-001	: 0000	C	1	0/14:43:05 - 0/14:44:35	1
36505	40014					
9	SUN	: 0000		1	0/14:45:15 - 0/14:49:35	1
40015	49491					
10	SUN	: 0000		1	0/14:55:05 - 0/14:59:25	1
49492	58968					
11	1148-001	: 0000	C	1	0/15:07:55 - 0/15:09:25	1
58969	62478					
12	SUN	: 0000		1	0/15:10:05 - 0/15:14:25	1
62479	71955					
13	SUN	: 0000		1	0/15:19:55 - 0/15:24:25	1
71956	81783					
14	1148-001	: 0000	C	1	0/15:32:55 - 0/15:34:25	1
81784	85293					
15	SUN	: 0000		1	0/15:35:05 - 0/15:39:25	1
85294	94770					
16	SUN	: 0000		1	0/15:44:55 - 0/15:49:25	1
94771	104598					
17	1148-001	: 0000	C	1	0/15:57:55 - 0/15:59:25	1
104599	108108					
18	SUN	: 0000		1	0/16:00:05 - 0/16:04:15	1
108109	117234					
19	SUN	: 0000		1	0/16:09:45 - 0/16:14:15	1
117235	127062					
20	1148-001	: 0000	C	1	0/16:22:45 - 0/16:24:15	1
127063	130572					
21	SUN	: 0000		1	0/16:24:55 - 0/16:29:15	1
130573	140049					

22 SUN	: 0000		1	0/16:34:45 -	0/16:39:15	1
140050	149877					
23 1148-001	: 0000	C	1	0/16:47:45 -	0/16:49:15	1
149878	153387					
24 SUN	: 0000		1	0/16:49:55 -	0/16:54:15	1
153388	162864					
25 SUN	: 0000		1	0/16:59:45 -	0/17:04:05	1
162865	172341					
26 1148-001	: 0000	C	1	0/17:12:35 -	0/17:14:05	1
172342	175851					
27 SUN	: 0000		1	0/17:14:45 -	0/17:19:05	1
175852	185328					
28 SUN	: 0000		1	0/17:24:35 -	0/17:29:05	1
185329	195156					
29 1148-001	: 0000	C	1	0/17:37:35 -	0/17:39:05	1
195157	198666					
30 SUN	: 0000		1	0/17:39:45 -	0/17:44:25	1
198667	208845					
31 SUN	: 0000		1	0/17:50:15 -	0/17:54:05	1
208846	217269					
32 1148-001	: 0000	C	1	0/18:02:25 -	0/18:03:55	1
217270	220779					
33 SUN	: 0000		1	0/18:04:35 -	0/18:08:55	1
220780	230256					
34 SUN	: 0000		1	0/18:14:25 -	0/18:18:55	1
230257	240084					
35 1148-001	: 0000	C	1	0/18:27:25 -	0/18:28:55	1
240085	243594					
36 SUN	: 0000		1	0/18:29:35 -	0/18:33:55	1
243595	253071					
37 SUN	: 0000		1	0/18:39:35 -	0/18:44:05	1
253072	262899					
38 1148-001	: 0000	C	1	0/18:52:35 -	0/18:53:55	1
262900	266058					
39 SUN	: 0000		1	0/18:54:45 -	0/18:59:05	1
266059	275535					
40 SUN	: 0000		1	0/19:04:25 -	0/19:08:45	1
275536	285012					
41 1148-001	: 0000	C	1	0/19:17:25 -	0/19:18:45	1
285013	288171					
42 SUN	: 0000		1	0/19:19:25 -	0/19:23:45	1
288172	297648					
43 SUN	: 0000		1	0/19:29:15 -	0/19:33:45	1
297649	307476					
44 1148-001	: 0000	C	1	0/19:42:15 -	0/19:43:45	1
307477	310986					
45 SUN	: 0000		1	0/19:44:25 -	0/19:53:05	1
310987	329589					
46 SUN	: 0000		1	0/19:54:25 -	0/19:58:45	1
329590	339066					
47 1148-001	: 0000	C	1	0/20:07:05 -	0/20:08:35	1

339067	342576								
48 SUN		: 0000		1	0/20:09:15	-	0/20:13:35		1
342577	352053								
49 SUN		: 0000		1	0/20:19:05	-	0/20:23:35		1
352054	361881								
50 1148-001		: 0000	C	1	0/20:32:05	-	0/20:33:35		1
361882	365391								
51 SUN		: 0000		1	0/20:34:15	-	0/20:38:35		1
365392	374868								
52 SUN		: 0000		1	0/20:44:05	-	0/20:48:35		1
374869	384696								
53 1148-001		: 0000	C	1	0/20:57:05	-	0/20:58:35		1
384697	388206								
54 SUN		: 0000		1	0/20:59:15	-	0/21:03:35		1
388207	397657								
55 SUN		: 0000		1	0/21:08:55	-	0/21:13:25		1
397658	407485								
56 1148-001		: 0000	C	1	0/21:21:55	-	0/21:23:25		1
407486	410969								
57 SUN		: 0000		1	0/21:24:05	-	0/21:28:25		1
410970	420446								
58 SUN		: 0000		1	0/21:33:55	-	0/21:38:25		1
420447	430274								
59 1148-001		: 0000	C	1	0/21:47:05	-	0/21:48:25		1
430275	433433								
60 SUN		: 0000		1	0/21:49:05	-	0/21:53:25		1
433434	442858								
61 SUN		: 0000		1	0/21:58:55	-	0/22:03:25		1
442859	452686								
62 1148-001		: 0000	C	1	0/22:11:45	-	0/22:13:15		1
452687	456196								
63 SUN		: 0000		1	0/22:13:55	-	0/22:18:15		1
456197	465647								
64 SUN		: 0000		1	0/22:23:55	-	0/22:28:15		1
465648	475124								
65 1148-001		: 0000	C	1	0/22:36:55	-	0/22:38:15		1
475125	478283								
66 SUN		: 0000		1	0/22:38:55	-	0/22:43:15		1
478284	487734								
67 SUN		: 0000		1	0/22:48:55	-	0/22:53:25		1
487735	497562								
68 1148-001		: 0000	C	1	0/23:01:55	-	0/23:03:15		1
497563	500721								
69 SUN		: 0000		1	0/23:03:55	-	0/23:08:05		1
500722	509847								
70 SUN		: 0000		1	0/23:13:45	-	0/23:18:05		1
509848	519324								
71 1148-001		: 0000	C	1	0/23:26:45	-	0/23:28:05		1
519325	522249								
72 SUN		: 0000		1	0/23:28:45	-	0/23:33:05		1

```

522250      531700
  73 SUN                : 0000          1 0/23:38:45 - 0/23:43:05    1
531701      540450
  74 1148-001          : 0000 C          1 0/23:51:45 - 0/23:53:05    1
540451      543350
  75 SUN                : 0000          1 0/23:53:45 - 0/23:58:05    1
543351      552125
  76 SUN                : 0000          1 1/00:01:15 - 1/00:01:15    1
552126      552450
  77 SUN                : 0000          1 1/00:07:25 - 1/00:07:55    1
552451      553725
  78 3C286             : 0000 B          1 1/00:21:35 - 1/00:22:55    1
553726      556884

```

Source summary

Velocity type = ' ' Definition = ' '

ID	Source	Qual	Calcode	RA( 0.0)	Dec( 0.0)	IFlux
1	1148-001	: 0000	C	11:48:10.1300	-00:07:13.300	0.000
0.000	0.000	0.000		84072		
2	SUN	: 0000		12:10:30.1272	-01:08:22.648	0.000
0.000	0.000	0.000		469653		
3	3C286	: 0000	B	13:28:49.6570	30:45:58.640	0.000
0.000	0.000	0.000		3159		

ID	Source	Freq(GHz)	Velocity(Km/s)	Rest freq (GHz)
1	All Sources	1.4462	0.0000	0.0000

Frequency Table summary

FQID	IF#	Freq(GHz)	BW(kHz)	Ch.Sep(kHz)	Sideband
1	1	1.44615001	12500.0010	12500.0010	1

AIPS 1: Resumes

# PRTAN

Print the Antenna positions — useful for thinking about calibration.

go prtan

```

v1b054      PRTAN(31DEC08)    100    14-NOV-2008  21:45:10    Page    1
File=19810926  .L BAND.      1    An.ver=  1    Vol=  1    User= 100
Array= VLA      Freq= 1446.150006 MHz    Ref.date= 26-SEP-1981

```

Array reference position in meters (Earth centered)

```

Array BX= -1601185.36500    BY= -5041977.54700    BZ=  3554875.87000
Polar X =  0.00000 Polar Y =  0.00000 arcsec
Earth rotation rate = 360.9856449713 degrees / IAT day
GST at UT=0 = 364.7139688925 degrees

```

UT1-UTC= 0.0000000 Data time(IAT )-UTC= 0.0000000 seconds  
 Solutions not yet determined for a particular FREQID

Ant 1 = VLA:\_N2 BX= -30.0602 BY= -4.7835 BZ= 45.7022  
 Mount=ALAZ Axis offset= 0.0000 meters IFA IFB  
 Feed polarization type = R L

Ant 2 = VLA:\_E5 BX= 51.8719 BY= 195.8466 BZ= -75.1013  
 Mount=ALAZ Axis offset= 0.0000 meters IFA IFB  
 Feed polarization type = R L

Ant 3 = VLA:\_E9 BX= 139.6430 BY= 536.8956 BZ= -207.7424  
 Mount=ALAZ Axis offset= -0.0033 meters IFA IFB  
 Feed polarization type = R L

Ant 4 = VLA:\_E6 BX= 70.6548 BY= 267.7575 BZ= -102.8996  
 Mount=ALAZ Axis offset= 0.0078 meters IFA IFB  
 Feed polarization type = R L

Ant 5 = VLA:\_N3 BX= -52.4373 BY= -8.2629 BZ= 78.6643  
 Mount=ALAZ Axis offset= 0.0000 meters IFA IFB  
 Feed polarization type = R L

Ant 6 = VLA:\_W2 BX= 14.7735 BY= -37.1404 BZ= -20.2135  
 Mount=ALAZ Axis offset= 0.0000 meters IFA IFB  
 Feed polarization type = R L

Ant 7 = VLA:\_W3 BX= 28.9195 BY= -74.4876 BZ= -41.0524  
 Mount=ALAZ Axis offset= -0.0036 meters IFA IFB  
 Feed polarization type = R L

Ant 8 = VLA:\_W1 BX= 22.9920 BY= 3.4974 BZ= -32.4864  
 Mount=ALAZ Axis offset= 0.0084 meters IFA IFB  
 Feed polarization type = R L

Ant 9 = VLA:\_E2 BX= 11.3328 BY= 40.6638 BZ= -15.1624  
 Mount=ALAZ Axis offset= 0.0000 meters IFA IFB  
 Feed polarization type = R L

Ant 10 = VLA:\_OUT BX= 0.0000 BY= 0.0000 BZ= 0.0000  
 Mount=ALAZ Axis offset= 0.0000 meters IFA IFB  
 Feed polarization type = R L

Ant 11 = VLA:\_E8 BX= 114.4257 BY= 438.6941 BZ= -169.4880  
 Mount=ALAZ Axis offset= 0.0048 meters IFA IFB  
 Feed polarization type = R L

Ant 12 = VLA:\_E3 BX= 21.9945 BY= 81.5250 BZ= -30.9498  
 Mount=ALAZ Axis offset= 0.0000 meters IFA IFB  
 Feed polarization type = R L



Ant 13 = VLA:_E7	BX= 91.5227	BY= 348.8871	BZ= -134.4449
Mount=ALAZ	Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =		R	L
Ant 14 = VLA:_W7	BX= 121.6261	BY= -319.1264	BZ= -177.5842
Mount=ALAZ	Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =		R	L
Ant 15 = VLA:_W9	BX= 186.8061	BY= -491.1158	BZ= -273.5624
Mount=ALAZ	Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =		R	L
Ant 16 = VLA:_E4	BX= 35.6150	BY= 133.6310	BZ= -51.1099
Mount=ALAZ	Axis offset= -0.0051 meters	IFA	IFB
Feed polarization type =		R	L
Ant 17 = VLA:_W8	BX= 152.7524	BY= -401.2839	BZ= -223.4146
Mount=ALAZ	Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =		R	L
Ant 18 = VLA:_E1	BX= 45.3386	BY= 7.0026	BZ= -65.4888
Mount=ALAZ	Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =		R	L
Ant 19 = VLA:_N7	BX= -193.6105	BY= -30.2503	BZ= 286.4580
Mount=ALAZ	Axis offset= -0.0030 meters	IFA	IFB
Feed polarization type =		R	L
Ant 20 = VLA:_N1	BX= 0.6703	BY= 0.0144	BZ= 0.5135
Mount=ALAZ	Axis offset= 0.0045 meters	IFA	IFB
Feed polarization type =		R	L
Ant 21 = VLA:_N8	BX= -243.6039	BY= -38.0389	BZ= 360.0340
Mount=ALAZ	Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =		R	L
Ant 22 = VLA:_W5	BX= 68.6012	BY= -179.2282	BZ= -99.5242
Mount=ALAZ	Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =		R	L
Ant 23 = VLA:_N5	BX= -108.4301	BY= -16.9862	BZ= 161.0152
Mount=ALAZ	Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =		R	L
Ant 24 = VLA:_N9	BX= -298.3837	BY= -46.5620	BZ= 440.6260
Mount=ALAZ	Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =		R	L
Ant 25 = VLA:_N6	BX= -148.4545	BY= -23.2162	BZ= 219.9871
Mount=ALAZ	Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =		R	L

```

Ant 26 = VLA:_N4 BX=      -74.8318 BY=      -11.7331 BZ=      111.6208
Mount=ALAZ Axis offset= 0.0000 meters IFA      IFB
Feed polarization type = R      L

Ant 27 = VLA:_W6 BX=      93.5170 BY=     -245.0012 BZ=     -136.2284
Mount=ALAZ Axis offset= 0.0000 meters IFA      IFB
Feed polarization type = R      L

Ant 28 = VLA:_W4 BX=      46.9220 BY=     -122.0267 BZ=     -67.6047
Mount=ALAZ Axis offset= 0.0000 meters IFA      IFB
Feed polarization type = R      L

Ant 29 = VPT:_OUT BX=      0.0000 BY=      0.0000 BZ=      0.0000
Mount=ALAZ Axis offset= 0.0000 meters IFA      IFB
Feed polarization type = R      L

```

Location Of VLA Antennas

```

          N9 (24)
          N8 (21)
          N7 (19)
          N6 (25)
          N5 (23)
          N4 (26)
          N3 ( 5)
          N2 ( 1)
          N1 (20)
      ( 8) W1   E1 (18)
    ( 6) W2     E2 ( 9)
  ( 7) W3       E3 (12)
(28) W4         E4 (16)
(22) W5         E5 ( 2)
(27) W6         E6 ( 4)
(14) W7         E7 (13)
(17) W8         E8 (11)
(15) W9         E9 ( 3)
          VLA:_OUT (10)
          VPT:_OUT (29)

```

AIPS 1: Resumes

The really important part for you, the data reducer, is the antenna layout at the bottom. This tells you in a nice graphical form where each antenna is located. This helps you to figure out which baselines are small, and which baselines are long. This is also useful for figuring out other things related to antenna position and baseline direction.

```

vlb054  LISTR(31DEC08)  100  14-NOV-2008  22:05:45  Page  1
File = 19810926  .L BAND.  1 Vol = 1  Userid = 100  Channels = 1- 1
IF = 1
Freq= 1.446150006 GHz  Ncor= 1  No. vis= 3159

```

Stokes = RR Subarray = 1

Source=3C286 : 0000, Stokes=RR , IF= 1, Chans= 1- 1  
Flux = 0.0000 Jy, Calcode = B , Freq = 1.446150006 GHz  
Amplitudes, 1000 = 1.000 Jy, averging type = Vector

Baselines 1 3 2 3 3 4 3 5 3 6 3 7 3 8 3 9 310 311 312 313 314 315 316  
317 318 319 320 321 322 323 324 325 326 327 328 329

1/00:21:35 293 259 258 282 45 360 431 333 563 326 247 264 256 469  
287 127 283 84 56 455 12 344 307 313 321 347

Amplitudes, 1000 = 10.000 Jy, averging type = Vector

1/00:21:45 195 180 182 168 15 212 234 203 247 135 160 177 169 187  
174 156 178 129 66 205 1 185 186 189 158 158

1/00:21:55 206 196 194 176 67 223 246 214 252 139 169 192 183 193  
183 185 190 188 205 214 1 192 199 199 165 168

1/00:22:05 209 197 197 179 165 223 246 217 251 144 172 193 185 194  
186 186 193 190 235 216 1 193 201 202 167 169

1/00:22:15 205 194 196 178 198 223 244 214 246 140 170 189 182 193  
183 186 190 190 235 212 0 193 198 199 164 169

1/00:22:25 206 192 197 177 196 222 243 214 242 139 165 189 180 193  
183 184 190 186 231 212 1 191 197 199 164 168

1/00:22:35 207 195 196 178 198 223 246 215 240 140 166 192 182 192  
184 185 190 190 233 214 0 192 199 199 165 168

1/00:22:45 206 192 192 177 199 222 243 213 232 141 168 191 183 190  
183 185 191 187 233 214 1 191 197 198 164 169

1/00:22:55 206 193 195 179 199 223 243 213 230 140 170 190 182 193  
183 185 190 186 233 215 1 191 197 199 164 169

AIPS 1: Resumes

v1b054 LISTR(31DEC08) 100 14-NOV-2008 22:35:27 Page 1  
File = 19810926 .L BAND. 1 Vol = 1 Userid = 100 Channels = 1- 1  
IF = 1  
Freq= 1.446150006 GHz Ncor= 1 No. vis= 84072  
Stokes = RR Subarray = 1  
Applying flag table 1

Source=1148-001 : 0000, Stokes=RR , IF= 1, Chans= 1- 1  
Flux = 0.0000 Jy, Calcode = C , Freq = 1.446150006 GHz  
Amplitudes, 1000 = 10.000 Jy, averging type = Vector

Baselines 1 3 2 3 3 4 3 5 3 6 3 7 3 8 3 9 310 311 312 313 314 315 316  
317 318 319 320 321 322 323 324 325 326 327 328 329

0/13:53:55 57 126 58 53 86 123 73 195 32 57 13 23 66  
30 36 27 75 30 89 24 20 28 45 103

0/13:54:05 67 134 66 24 65 155 47 213 26 66 28 28 92  
30 53 35 60 26 63 28 33 55 77 103

0/13:54:15 43 124 77 29 43 26 144 44 184 36 77 40 29 96  
19 39 29 34 31 34 26 34 76 62 134

0/13:54:25 6 104 91 62 40 68 96 73 177 59 93 30 30 87

```

35  4 26 41 45 78      32 31 74 14 139
    0/13:54:35 28 84 94 70 21 93 69 80      191 56 104 19 31 61
34 50 31 68 42 94      31 24 41 46 99

```

Source=1148-001 : 0000, Stokes=RR , IF= 1, Chans= 1- 1  
 Flux = 0.0000 Jy, Calcode = C , Freq = 1.446150006 GHz  
 Amplitudes, 1000 = 10.000 Jy, averging type = Vector

```

Baselines      1 3 2 3 3 4 3 5 3 6 3 7 3 8 3 9 310 311 312 313 314 315 316
317 318 319 320 321 322 323 324 325 326 327 328 329
    0/14:18:25 37 65 58 31      101 107 83      230 68 57 35 34 81
33  90 40 56 18 32      32 45 69 32 47
    0/14:18:35  4 65 55 22      78 85 80      191 67 58 28 28 78
26  58 28 58 33 50      29 39 28 17 39
    0/14:18:45 36 62 56 30 17 32 45 47      128 48 57 28 32 61
32  48 24 31 44 48      34 26 18 29 17
    0/14:18:55 54 54 70 40 24 39 15 18      194 27 61 30 36 28
33  80 34  6 45 27      34 25 52 36 35
    0/14:19:05 48 27 87 54 30 90 70 24      176 21 56 29 47 14
39 114 42 29 50 42      43 44 63 24 47
    0/14:19:15 38  7 105 40 33 117 116 67      113 59 63 42 43 51
44 105 45 70 51 62      44 58 66 29 39
    0/14:19:25 23 48 112 35 30 75 117 92      198 80 50 46 44 84
46  57 38 74 59 63      47 48 21 50 30
    0/14:19:35 58 72 99 36 26 39 70 66      123 60 31 38 40 86
34  35 41 42 49 31      42 27 33 46 35

```

Source=1148-001 : 0000, Stokes=RR , IF= 1, Chans= 1- 1  
 Flux = 0.0000 Jy, Calcode = C , Freq = 1.446150006 GHz  
 Amplitudes, 1000 = 10.000 Jy, averging type = Vector

```

Baselines      1 3 2 3 3 4 3 5 3 6 3 7 3 8 3 9 310 311 312 313 314 315 316
317 318 319 320 321 322 323 324 325 326 327 328 329
    0/14:43:25 32 32 95 40      47 27 55      237 14 83 30 33 58
31  33 38 40 20 35      34 35 13 28 35
    0/14:43:35 34 56 91 30      44 48 60      173 29 80 34 33 46
32  29 36 38 35 37      34 33 38 29 37
    0/14:43:45 27 59 103 14 27 21 51 54      130 51 66 25 25 72
24  23 22 14 27 26      21 23 48 23 26
    0/14:43:55 22 49 112 29 24 18 35 23      182 49 43 19 26 95
23  30 20  9 30 28      27 22 32 20 21
    0/14:44:05 39 59 141 41 28 42 36  2      163 35 32 32 33 112
31  32 37 35 41 35      34 35 29 30 30
    0/14:44:15 36 49 157 37 23 50 28 29      179 16 17 31 32 98
32  31 38 44 36 34      29 33 18 28 35
    0/14:44:25 27 28 159 25 22 37 38 54      200 17 17 30 29 71
28  26 27 38 33 31      27 28 36 28 31
    0/14:44:35 28  1 150 20 31 23 47 60      242 39 22 29 30 42
28  29 27 22 39 34      30 29 51 28 27

```

Source=1148-001 : 0000, Stokes=RR , IF= 1, Chans= 1- 1  
 Flux = 0.0000 Jy, Calcode = C , Freq = 1.446150006 GHz  
 Amplitudes, 1000 = 10.000 Jy, averging type = Vector

Baselines	1	3	2	3	3	4	3	5	3	6	3	7	3	8	3	9	310	311	312	313	314	315	316	
317 318 319 320 321 322 323 324 325 326 327 328 329																								
0/15:08:15	17	35	52	25					33	42	35						148	14	29	28	29	49		
29 31 30 27 15 38				29	32	35	25	33																
0/15:08:25	29	38	64	22					27	33	32						146	14	38	27	25	52		
25 31 33 18 29 30				27	22	23	22	35																
0/15:08:35	33	25	70	27	23	25	27	25									135	25	35	21	25	49		
21 29 26 17 30 25				24	19	18	18	29																
0/15:08:45	50	35	91	34	35	42	44	43									185	32	52	37	34	49		
34 34 30 38 45 40				36	39	43	33	33																
0/15:08:55	30	28	84	30	32	37	43	34									188	26	53	32	33	26		
32 26 29 42 37 40				32	36	41	27	26																
0/15:09:05	21	27	72	28	31	37	46	35									185	26	56	31	32	9		
31 27 37 36 37 39				32	30	35	29	35																

vlb054 LISTR(31DEC08) 100 14-NOV-2008 22:36:24 Page 1  
 File = 19810926 .L BAND. 1 Vol = 1 Userid = 100 Channels = 1- 1  
 IF = 1  
 Freq= 1.446150006 GHz Ncor= 1 No. vis= 84072  
 Stokes = RR Subarray = 1  
 Applying flag table 1

Source=1148-001 : 0000, Stokes=RR , IF= 1, Chans= 1- 1  
 Flux = 0.0000 Jy, Calcode = C , Freq = 1.446150006 GHz  
 Phase, 1000 = 1000.00 degrees, averging type = Vector

Baselines	1	3	2	3	3	4	3	5	3	6	3	7	3	8	3	9	310	311	312	313	314	315	316	
317 318 319 320 321 322 323 324 325 326 327 328 329																								
0/13:53:55	-154	176	177	-145					82	59	-83						-35	-118	-77	101	41	3		
59 63 114 69 -97 80				76	88	-57	67	121																
0/13:54:05	163	138	-130	-83					141	119	-21						-20	-30	-50	52	43	52		
78 97 122 122 -106 147				78	88	46	166	-137																
0/13:54:15	127	100	-91	65	-134	-101	172	78									-173	44	-26	79	44	90		
51 137 129 -158 -129 -79				72	102	95	-124	-55																
0/13:54:25	118	61	-61	125	-91	13	-128	145									172	105	-3	99	45	126		
51 -125 122 -51 -119 21				73	111	140	2	12																
0/13:54:35	-125	9	-32	168	-49	68	-31	-164									161	144	17	64	39	167		
75 31 115 12 -106 79				77	97	-174	142	90																

Source=1148-001 : 0000, Stokes=RR , IF= 1, Chans= 1- 1  
 Flux = 0.0000 Jy, Calcode = C , Freq = 1.446150006 GHz  
 Phase, 1000 = 1000.00 degrees, averging type = Vector

Baselines	1	3	2	3	3	4	3	5	3	6	3	7	3	8	3	9	310	311	312	313	314	315	316	
317 318 319 320 321 322 323 324 325 326 327 328 329																								
0/14:18:25	135	174	69	167					66	121	-173						51	109	26	75	39	58		

```
61 136 118 27-117 30 73 88 140-157 -8
0/14:18:35 -72 153 124 160 123 168-128 93 145 32 67 42 93
49-154 126 72-128 56 67 111-158 177 13
0/14:18:45 -131 132 173 146-116-171-153 -91 147-177 42 68 36 129
50 -56 105 107-120 83 73 112 25 160 -43
0/14:18:55 -165 103-132 149-123 -19 -9 -18 6-122 55 73 40 167
61 23 101-175-110 89 76 81 66-175 -41
0/14:19:05 162 87 -88 160-120 46 81 143 -37 33 72 73 37 23
53 78 112 -3-118 46 73 83 112-159 -16
0/14:19:15 141 -86 -66 164-116 89 113 174 -114 69 87 66 40 22
49 120 122 26-126 54 73 98 143 165 -7
0/14:19:25 -137-143 -42 155-114 141 151-151 118 111 94 69 35 50
56 167 112 65-120 78 73 111 155 166 -18
0/14:19:35 -139-164 -20 142-130 -91-161-118 166 144 107 72 37 79
55 -66 99 109-114 88 78 99 37-168 -38
```

Source=1148-001 : 0000, Stokes=RR , IF= 1, Chans= 1- 1  
Flux = 0.0000 Jy, Calcode = C , Freq = 1.446150006 GHz  
Phase, 1000 = 1000.00 degrees, averging type = Vector

```
Baselines 1 3 2 3 3 4 3 5 3 6 3 7 3 8 3 9 310 311 312 313 314 315 316
317 318 319 320 321 322 323 324 325 326 327 328 329
0/14:43:25 -174-121 103 162 65 109 166 41 37 70 66 32-169
49 86 97 42-121 64 64 91 89-178 -29
0/14:43:35 -169-148 150 173 81 104-159 138 70 88 65 32 -85
48 76 109 66-129 60 67 92 71 178 -20
0/14:43:45 -165-171-168 150-127 97 120-123 116 107 114 64 28 -20
54 69 109 87-132 61 56 94 90 170 -18
0/14:43:55 -170 163-127 133-123 58 147 -84 90 142 139 68 35 32
53 74 91 6-133 61 58 85 121 175 -25
0/14:44:05 -177 139 -92 148-112 53 149 -32 72 177 164 69 35 70
47 82 97 19-127 64 64 90 134-174 -30
0/14:44:15 180 123 -62 162-122 68 116 147 62-116-143 65 32 105
54 81 109 35-124 64 66 90 87 175 -30
0/14:44:25 -176 101 -37 168-136 85 105 177 51 15 -85 66 30 145
50 76 112 59-132 57 64 88 72 171 -20
0/14:44:35 -162 105 -7 146-133 79 117-152 41 68 -46 68 30-163
47 71 96 67-132 61 59 87 97 173 -24
```

Source=1148-001 : 0000, Stokes=RR , IF= 1, Chans= 1- 1  
Flux = 0.0000 Jy, Calcode = C , Freq = 1.446150006 GHz  
Phase, 1000 = 1000.00 degrees, averging type = Vector

```
Baselines 1 3 2 3 3 4 3 5 3 6 3 7 3 8 3 9 310 311 312 313 314 315 316
317 318 319 320 321 322 323 324 325 326 327 328 329
0/15:08:15 -152 172-105 148 73 125-161 -32 127 -46 69 28 39
48 65 87 38-129 62 62 93 108 179 -40
0/15:08:25 -136 152 -86 139 76 126-157 -27 89 -36 66 28 63
53 80 95 41-139 66 61 96 114 175 -30
0/15:08:35 -164 140 -63 149-130 64 135-148 -15 107 -11 67 22 87
```

```

50  78 114  9-134  60      67  80  93 177 -17
    0/15:08:45 178 144 -39 151-126 66 128-148      -3 119  9  68  28 106
51  90 108 12-127  58      65  82  91-177 -16
    0/15:08:55 167 150 -18 151-124 70 124-149      9 132 23  69  27 121
48  70  87 27-127  57      62  87 101-179 -33
    0/15:09:05 -160 162  3 151-129 72 126-157     21 135 33  65  28  74
51  48  93 40-134  67      61  96 111 177 -36

```

## SETJY

```

task 'setjy'
source '3c286', ' '
optype 'calc'
aparm(2)=3
go

```

```

vlb054> SETJY1: Task SETJY (release of 31DEC08) begins
vlb054> SETJY1: **WARNING: OPCODE=CALC AND FREQID = -1
vlb054> SETJY1:      FREQID WILL BE RESET TO 1, CHECK YOUR RESULTS CAREFULLY
vlb054> SETJY1: A source model for this calibrator may be available
vlb054> SETJY1: Use the verb CALDIR to see if there is one
vlb054> SETJY1: / Flux calculated using known spectrum
vlb054> SETJY1: BIF = 1 EIF = 1 /Range of IFs
vlb054> SETJY1: '3C286      ' IF = 1 FLUX =14.5979 (Jy calcd)
vlb054> SETJY1: / Using (1990) VLA or Reynolds (1934-638) coefficients
vlb054> SETJY1: Appears to have ended successfully
vlb054> SETJY1: vlb054      31DEC08 TST: Cpu=      0.0  Real=      0

```

## CALRD

```

task 'calrd'
object '3c286'
band 'l'
go

```

```

vlb054> CALRD1: Task CALRD (release of 31DEC08) begins
vlb054> CALRD1: Reading disk file AIPSTARS:3C286_L.MODEL
vlb054> CALRD1: Create 3C286_L      .MODEL .  1 (MA)  on disk  1  cno  5
vlb054> CALRD1: Appears to have ended successfully
vlb054> CALRD1: vlb054      31DEC08 TST: Cpu=      0.0  Real=      0

```

So it looks like the calibration data image was put into catalog entry number 5.

## CALIB

```
task 'calib'  
getn 2  
calsour '3c286', ' '  
uvrange 0  
antennas 0  
refant 24  
weightit 1  
in2di 1  
get2n 5  
ncomp 0  
solmode 'A&P'  
aparm(6) 2  
minamper 10  
minphser 10  
docalib 1  
solint 1  
solsub 2  
cparm(3) 10  
cparm(4) 10
```

From:  
<https://www.astron.nl/lofarwiki/> - **LOFAR Wiki**

Permanent link:  
[https://www.astron.nl/lofarwiki/doku.php?id=public:meetings:glowbi2008:tutorial\\_monday&rev=1226699119](https://www.astron.nl/lofarwiki/doku.php?id=public:meetings:glowbi2008:tutorial_monday&rev=1226699119)

Last update: **2008-11-14 21:45**

